



影驰主板

BIOS 升级教程

V1.0

注意: 更新 BIOS 存在一定的风险, 请务必确认您的主板型号与 BIOS 正确, 否则请勿刷新。

刷新过程中请不要切断电源或重启电脑, 否则将导致刷新失败。

本操作需要在 DOS 环境下完成, 如果您对 DOS 操作不熟悉, 请连系经销商或相关专业人士进行现场操作

步骤:

1. 关闭 BIOS 写保护: 开机在机器自检过程中按 DEL 键进入 BIOS。进入 Starup, 将 BIOS Write Protection 改为 Disable 后 F10 保存退出。

2. 将附件中的所有文件, 拷贝到您的 DOS 工具盘或硬盘的分区根目录下 (Fat32 分区)

名称	修改日期	类型	大小
f	2017/7/25 11:56	Windows 批处理...	1 KB
fparts	2015/7/6 21:04	文本文档	11 KB
FPT	2015/7/3 0:39	应用程序	1,607 KB
WXH110.014	2017/7/25 10:28	014 文件	8,192 KB

3. 通过工具盘将您的机器引导到 DOS 下, 输入 **f.bat 开始刷入 bios**

```
Start booting from USB device...
MS-DOS 7.1 [Version 7.10.1999]
C:\>f.bat
```

4.刷新过程中请耐心等待，切勿断电

```
Start booting from USB device...
MS-DOS 7.1 [Version 7.10.1999]
C:\>f.bat
C:\>fpt -f MXH110.014
Intel (R) Flash Programming Tool. Version: 11.0.0.1160
Copyright (c) 2007 - 2015, Intel Corporation. All rights reserved.

Reading HSFSTS register... Flash Descriptor: Valid

o--- Flash Devices Found ---
oM25Q64BV oID:0xEF4017 oSize: 8192KB (65536Kb)

PDR Region does not exist.
GbE Region does not exist.

- Reading Flash [0x06F5C40] 7127KB of 8192KB - 87 percent complete
```

5.待 **FPT Operation Successful** 字样出现，恭喜您刷新 bios 成功，可按 Alt+Ctrl+Del

重启电脑

```
- Erasing Flash Block [0x18F000] - 100 percent complete.
- Programming Flash [0x018F000] 8KB of 8KB - 100 percent complete.
- Erasing Flash Block [0x1BE000] - 100 percent complete.
- Programming Flash [0x01BE000] 4KB of 4KB - 100 percent complete.
- Erasing Flash Block [0x1DC000] - 100 percent complete.
- Programming Flash [0x01DC000] 112KB of 112KB - 100 percent complete.
- Erasing Flash Block [0x1E0000] - 100 percent complete.
- Programming Flash [0x01E0000] 4KB of 4KB - 100 percent complete.
- Verifying Flash [0x0000000] 8192KB of 8192KB - 100 percent complete.
RESULT: The data is identical.

FPT Operation Successful.

C:\>
C:\>
C:\>_
```